



VZ-702M Lithium-Ion Battery Kit for VZ-TFT Monitors

Kit includes:



12V DC / 1A Step-up Cable (connects battery to monitor)

Warnings:

- Charge the battery pack only with the included AC adapter AND charging interface cable. Improper charging may result in damage or unsafe conditions.
- Do not expose the battery kit to moisture. Store only in a dry, cool place.
- Do not leave the battery kit in the sun for prolonged periods or charge it in direct sunlight.
- Do not attempt to disassemble the battery or other parts of the kit.
- Do not use the kit if the connecting wires are frayed or damaged.
- Do not enclose, wrap, tape or cover any of the components, as they produce heat. Obstructing the flow of air around the components may cause them to overheat.

Features:

- 5 LED battery life indicator (push button to check remaining battery life)
- Charging interface cable with LED indicator (Red-charging / Green-fully charged)
- Battery has integral 1/4"-20 screw and bottom thread-mount for sandwiching battery between TFT monitor and on-camera swivel shoe mount (also enables double stacking of batteries).
- Dual-purpose AC adapter for charging battery (with interface cable) or for powering VZ-TFT monitor directly from AC socket.

Charging:

1. Charge the battery before first use. Plug the output connector of the AC adapter (or car adapter) into the charging interface cable (A), and then plug the AC adapter into a 110-120V AC power outlet (or plug the car adapter into the outlet/cigarette lighter).
2. Now plug the output connector of the charging interface cable into the socket on the battery (B). The LED indicator on the charging interface cable will glow Red to let you know it is charging. Once charging is complete, the LED will turn green and you should disconnect the battery.



Connecting battery to TFT monitor:

1. Attach the battery to your TFT monitor by screwing the integral 1/4"-20 screw into the threaded hole on the bottom of the monitor. If you plan to mount the monitor on top of your camera, you can screw the swivel shoe mount into the bottom of the battery.
2. Connect the 12VDC/1A step-up cable to the battery using the plug marked "Battery". Plug the yellow-tipped end of the step-up cable (marked "12V DC Output") into the power jack on your TFT monitor.
3. The battery should power your TFT monitor for approximately 1.5 - 2 hours. You can stack two or three batteries underneath the monitor by screwing one into the monitor and then screwing another battery into the bottom of the first. When the first battery runs out, simply switch the plug to the fresh battery.



SPECIAL NOTE ABOUT POWERING THE TFT MONITOR WITH THE AC ADAPTER:

THE AC ADAPTER INCLUDED WITH YOUR VZ-702M KIT WILL POWER THE VZ-TFT MONITOR DIRECTLY. TO POWER THE MONITOR DIRECTLY FROM THE AC OUTLET, SIMPLY PLUG THE ADAPTER INTO THE WALL SOCKET AND INSERT THE OUTPUT CONNECTOR DIRECTLY INTO THE MONITOR POWER JACK. DO NOT USE THE CHARGING INTERFACE CABLE TO POWER THE MONITOR! THE CHARGING INTERFACE CABLE SHOULD ONLY BE USED TO CHARGE THE BATTERY.

Notes:

- It is normal for the charger, adapter and battery to become warm during operation.
- If either the charging interface cable or step-up cable do not seem to be working (the LED does not illuminate), simply unplug and re-plug the components so they can reset.
- Unplug the battery pack when not in use as connected devices will drain power even when turned off.
- All batteries naturally discharge over time even when not in use, so recharge the battery within a day of planned use for maximum power.

The VZ-702M battery kit is covered by a 90-day warranty (parts/labor). Please retain your receipt for warranty verification. All returns and repairs must be accompanied by a Return Merchandise Authorization number (RMA #). Contact us at 888-826-3399 / 512-219-7722 or at www.varizoom.com